# Panda 15000x PMS



Article: 0013445

## General Technical Data

#### Water-cooled Marine Generator

Generator Type xSeries - Compact Power

Generator Family 15000
Generator Version PMS
Area of Application Marine
Capsule Type GFK 3D

Generator Manufacturer Fischer Panda GmbH

Windings Isolation Class F

Control System xControl / fpControl

Voltage Tolerance 3V Cos Phi 0.85

Sound Levels dB(A) [7m/3m/1m] 54 / 64 / 68

Weight (kg) 248

Capsule Dimenisons (excl. fittings) 740 x 480 x 600



## **Electrical Alternator**

 Engine Speed [rpm]
 3000

 Voltage
 230

 Frequency [Hz]
 50

 Number Phases
 1

 Nominal Performance [kW]
 12,7

 Nominal Performance [kVA]
 15,0

#### **Engine**

Engine Manufacturer Kubota
Engine Type KU D902

 No. Cylinders
 3

 Displacement [cm3]
 898

 Starter System
 12 V

Emission Regulations IMO MARPOL 73/78

US 40CFR 1042 EU 2016/1628 China 20891-2014

## Service / Installations Kits/ Shock mountings

Service Kit 0000704

Service Kit "Plus"

Installation Kit "Basic" 0000677
Installation kit Premium 0000674
Shock mounting, captive 0002753
Shock mounting, non-captive 0009675

# Generator Capsule / Sound Shield







