# Panda 8000i PMS



Article: 0013236

## General Technical Data

#### Water-cooled Marine Generator

Generator Type iSeries - Perfect Power

Generator Family 8000i
Generator Version PMS
Area of Application Marine
Capsule Type GFK 3D

Generator Manufacturer Fischer Panda GmbH

Windings Isolation Class H
Control System iControl
Voltage Tolerance 3%
Cos Phi 0.80

Sound Levels dB(A) [7m/3m/1m]

Weight (kg) 105

Capsule Dimenisons (excl. fittings) 520 x 445 x 541



## **Electrical Alternator**

Engine Speed [rpm] 2200 - 2800

Voltage 120
Frequency [Hz] 60
Number Phases -/Nominal Performance [kW] 6,0
Nominal Performance [kVA] 7,5

#### **Engine**

Engine Manufacturer Kubota
Engine Type KU Z482

 No. Cylinders
 2

 Displacement [cm3]
 479

 Starter System
 12 V

Emission Regulations IMO MARPOL 73/78

US 40CFR 1042 EU 2016/1628 China 20891-2014

# Service / Installations Kits/ Shock mountings

Service Kit 0006353

Service Kit "Plus" 0006360

Installation Kit "Basic" 0000677

Installation kit Premium 0000674

Shock mounting, captive 0002750

Shock mounting, non-captive 0009675

# Generator Capsule / Sound Shield







