Panda 5000i PMS



Article: 0013227

General Technical Data

Water-cooled Marine Generator

Generator Type iSeries - Perfect Power

Generator Family 5000i
Generator Version PMS
Area of Application Marine
Capsule Type GFK 3D

Generator Manufacturer Fischer Panda GmbH

Windings Isolation Class H

Control System iControl

Voltage Tolerance 3%

Cos Phi 0.80

Sound Levels dB(A) [7m/3m/1m] 54 / 64 / 68Weight (kg) 82 + Inverter 9,7 Capsule Dimenisons (excl. fittings) $600 \times 399 \times 406$



Electrical Alternator

Engine Speed [rpm] 2200 - 2800

 Voltage
 230

 Frequency [Hz]
 50

 Number Phases
 1

 Nominal Performance [kW]
 4,0

 Nominal Performance [kVA]
 5,0

Engine

Engine Manufacturer Kubota
Engine Type KU EA300


 No. Cylinders
 1


 Displacement [cm3]
 309

 Starter System
 12 V

Emission Regulations IMO MARPOL 73/78

Generator Capsule / Sound Shield









Service / Installations Kits/ Shock mountings

Service Kit 0000688

Service Kit "Plus" 0006356

Installation Kit "Basic" 0000677

Installation kit Premium 0000674

Shock mounting, captive 0002750

Shock mounting, non-captive 0000678